

## 1.2.2 Pyroelectric Energy Sensors

### 1µJ to 10mJ

#### Features

- Ø12mm apertures
- Repetition rates up to 25,000Hz
- High sensitivity sensors
- Pulse widths up to 5ms

PE10-C / PE10BF-C



Model	PE10-C	PE10BF-C
<b>Use</b>	<b>Sensitive</b>	<b>High damage threshold</b>
Aperture mm	Ø12	Ø12
Absorber Type	metallic	BF
Spectral Range µm <sup>(a)</sup>	0.15 - 12	0.15 - 3, 10.6 <sup>(d)</sup>
Surface Reflectivity % approx.	50	20
Calibration Accuracy +/--% <sup>(a)</sup>	4	3
Max Pulse Width Setting <sup>(e)</sup>	1µs                      30µs	1ms                      5ms
Energy Scales	10mJ to 2µJ                      10mJ to 20µJ	10mJ to 20µJ                      10mJ to 200µJ
Lowest Measurable Energy µJ <sup>(c)</sup>	1	7
Max Pulse Width µs	1	1000
Maximum Pulse Rate pps	25kHz	5kHz
Noise on Lowest Range µJ	0.1	0.15
Additional Error with Frequency %	±2% to 15kHz, ±3% to 25kHz	±1% to 5kHz
Damage Threshold J/cm <sup>2</sup>		
< 100ns	0.1	0.8 <sup>(b)</sup>
1µs	0.2	1 <sup>(b)</sup>
300µs	3	4 <sup>(b)</sup>
Linearity with Energy <sup>(c)</sup>	±1.5%	±2%
Maximum Average Power W	2	3
Maximum Average Power Density W/cm <sup>2</sup>	50	50
Fiber Adapters Available (see page 102)	ST, FC, SMA, SC	ST, FC, SMA, SC
Weight kg	0.25	0.25
Compliance	CE, China RoHS	CE, China RoHS
Version		
<b>Part Number</b>	<b>7Z02932</b>	<b>7Z02938</b>
Note: (a) Calibrated curve is checked and adjusted at the following wavelengths (µm)	1.064, 0.355	0.193, 0.248, 0.355, 0.532, 1.064
For other wavelengths in the curve there is additional calibration error as stated.	240 - 800nm add ±4%, 2-3µm add ±8%, 10.6µm add ±15%. <240nm not calibrated	0.2-3µm ±2%, 10.6µm ±5%
Note: (b) For wavelengths below 600nm, derate damage threshold to 60% of given values. Below 300nm, derate to 40% of given values.		
Note: (c) For >7% of full scale, with the "user threshold" setting set to minimum. For other settings, the spec is for >7% of full scale or greater than twice the "user threshold", whichever is greater. The user threshold is not available with LaserStar, Nova/Orion, Pulsar, USBI and Quasar. For these meters, the threshold is set to minimum and the linearity spec is >10% of full scale. The PE-C series will only operate with Nova or Orion meters with an additional adapter Ophir P/N 7Z08272 (see page 103). The adapter can introduce up to 1% additional measurement error. The user threshold feature allows adjustment of the internal threshold up to 25% of full scale if desired to avoid false triggering in noisy environments. For further information, see the FAQs on our Website.		
Note: (d) The absorption at 675nm is approximately the same as at 10.6µm. Therefore, to measure a CO <sub>2</sub> laser, set to the 675nm setting. The additional error for measuring 10.6µm is ±5%.		
Note: (e) With the LaserStar, Pulsar, USBI, Quasar and Nova/Orion with adapter, for the PE10-C model the 1µs pulse width setting is displayed as "10µs".		

PE10-C / PE10BF-C

